

## Overview

This configuration guide assumes that the Skorpio X3 is using Windows CE 6.0. Similar settings are needed for any Windows Mobile or Embedded Operating Systems but the settings may be located in other configuration options. Remove any protective film that may be covering the barcode scan window.

NOTE: THESE SETTINGS ARE CRITICAL FOR PROPER OPERATION. DO NOT SKIP ANY SETTING.



## Touchscreen Calibration

If the touchscreen is not responding properly to stylus touch taps, the touchscreen may need to be recalibrated.

- 1) Tap the Start button in the lower left corner of the system tray.
- 2) Select Settings, then Control Panel.
- 3) Scroll the window if necessary and double tap the Stylus icon.
- 4) Select the "Calibration" tab.
- 5) Tap the "Recalibrate" button and follow the instructions on the screen.

## Set Date/Time/Time Zone

- 1) Tap the Start button in the lower left corner of the system tray.
- 2) Select Settings, then Control Panel.
- 3) Scroll the window if necessary and double tap the Date/Time icon.
- 4) Set the current date, time, and time zone.
- 5) Tap the Apply button and close the screen.

## Set Time Separator

- 1) In Control Panel, select Regional Settings.
- 2) Tap the Customize button.
- 3) Select the "Time" tab.
- 4) Set the Time Style to "h:mm:ss tt"
- 5) If the "Time Separator" is not the colon ":" character, select the Time Separator box.
- 6) Select the ":" character from the drop-down list (or type it in using the on-screen keyboard).
- 7) Tap the "OK" button at the top of the screen.

## Set Short Date Format

- 1) In Control Panel, select Regional Settings.
- 2) Tap the Customize button.
- 3) Select the "Date" tab.
- 4) Set the Short Date Style to "MM/dd/yyyy".
- 5) If the "Date Separator" is not the "/" character, select the Date Separator box.
- 6) Select the "/" character from the drop-down list (or type it in using the on-screen keyboard).
- 7) Tap the "OK" button at the top of the screen.

## Append **ONLY** the Carriage Return to Barcode scan

The default setting of the Skorpio X3 includes BOTH the Carriage Return [CR] and a Line Feed [LF]. The [LF] will interfere with proper scanning output. You must remove the [LF] following the steps below.

- 1) In Control Panel, select Decoding.
- 2) Tap Configure on the Menu and select Decoding Options.
- 3) Using the Right Arrow on the Menu, tap the Arrow until the Formatting page is displayed.
- 4) Select the Label Suffix radio button (NOT Prefix).
- 5) In the Edit Label Suffix window should be displayed [CR][LF].

- 6) Tap the window after the last character [LF] and press the BKSP (backspace) key to delete the [LF] only. The **[CR]** should be the only remaining Suffix. If there is no Suffix shown, select [CR] from the Add special dropdown listing and press **Add**.
- 7) Once only the Label Suffix [CR] is displayed, select "OK" at the top of the screen.

### ***Microsoft Active Sync Installation (For Windows XP)***

- 1) Locate a copy of the latest version of Active Sync for your computer system. The correct version is available from Microsoft's WEB site or a copy is included on your CD. Version 4.5 is the latest from Microsoft as of this printing.
- 2) Look for the installation file (i.e. activesync\_setup.msi) and run it. We recommend that you follow the installation instructions and accept the standard default settings during your install.
- 3) Leave Active Sync running to install and connect your handheld computer.

NOTE: Some users may use a single PC to connect multiple handheld computers. If this is the case, it is best to setup your PC to recognize each handheld as a "Guest". This avoids having Active Sync loading shared data from your Outlook and other PC applications. To set all connected handhelds as a Guest, please double-click and run the provided "GuestOnly.reg" file. It will instantly update your system for future connections.

### ***Windows Mobile Device Center Installation (For Windows Vista or Windows 7)***

- 1) Locate a copy of the latest version of Windows Mobile Device Center for your computer system. The correct version is available from Microsoft's WEB site or a copy is included on your download.
- 2) Look for the installation file (i.e. drvupdate-x86.exe) and run it. We recommend that you follow the installation instructions and accept the standard default settings during your install.
- 3) Select the "Connect without setting up your device" option. DO NOT setup your device to sync your contacts, pictures, etc. since this will limit the amount of memory available in the Skorpio X3.

Connect the USB cable to your PC and the handheld or docking station (if provided). Windows will locate the hardware and complete the installation.

### ***Install GigaTrak Handheld Application***

The handheld application can be found in the Handheld folder of your installation files.

- 1) Connect the handheld docking station to your computer (typically a USB connection) and plug in the AC power cable.
- 2) Put the handheld in the dock and wait for it to sync with the PC.
- 3) On the PC, double-click the handheld setup file for the application you are installing (e.g., setup\_skorpio\_hh.exe). The application will be installed in the "FlashDisk" on the Skorpio.

### ***Add a Shortcut to your Handheld Desktop***

The shortcut should be installed already in your Start/Programs listing. If not, you can perform the following.

- 1) Exit the application if it is running.
- 2) Double tap the 'My Device' icon on the desktop.
- 3) Double tap the "FlashDisk" icon.
- 4) Scroll down to the GigaTrak application icon (e.g., WIN-TTS).
- 5) Hold your stylus down on the icon until a pop-up menu appears.
- 6) Select 'Copy' on the menu.
- 7) Close the window to go back to the desktop.
- 8) Hold down the stylus on the desktop until a pop-up menu appears.
- 9) Select 'Paste Shortcut' from the menu.

## Resetting the Skorpio X3

There are several reset methods for the Skorpio X3.

A warm boot terminates an unresponsive application and clears the working RAM, but preserves the file system. The Registry is restored from persistent memory if available or returned to factory default.

A cold boot forces all applications to close reinitializing completely the system. It clears the working RAM, but the file system is preserved. The Registry is restored from persistent memory.

## Warm Boot the Handheld

To perform a Warm Boot press the **Yellow**, **Blue**, and the **ESC** keys simultaneously.



## Cold Boot the Handheld

To perform a cold boot, do the following steps:

- 1) Turn off the Skorpio X3 by pressing the ON/OFF Power button.
- 2) Pull the battery latch down and remove the battery pack.
- 3) Simultaneously press the SCAN key and the Reset button in the battery compartment.
- 4) Insert the battery pack.
- 5) Turn on the Skorpio X3 by pressing the ON/OFF Power button.